

D-Fi USB 2

Streamline your lighting setup with the improved version of our proprietary USB wireless DMX transceiver: D-Fi USB 2. New LED indicators simplify channel selection. Its single-material plastic housing is sleek and ideal for signal transmission. Enjoy the convenience of wireless connection that eliminates the need for DMX cables with this handy device powered directly from your CHAUVET DJ lighting fixture's USB port. This easy-to-use D-Fi solution makes setup time a breeze.

HIGHLIGHTS

- Finger-sized wireless D-Fi transceiver provides instant wireless communication
- No more dipswitches make channel selection easier and compatible with D-Fi XLR
- Transfers DMX / ILS as well as master/slave signals between similar fixtures
- Eliminates the need for DMX cables
- Plugs directly into USB and ILS-compatible devices
- Works without the need for an external power supply
- Fully FCC/RED compliant



SPECIFICATIONS

- DMX Channels : Operating Frequency: 2.412 to 2.484 GHz
- Max Unobstructed Distance : 165 ft (50 m)
- Operating Frequency : 2.412 to 2.484 GHz
- Input Voltage : 5 VDC
- Weight : 0.7 oz (20 g)
- Size : 3.2 x 0.9 x 0.55 in (81.5 x 25 x 14.2 mm)
- Approvals : CE, UKCA, RoHS, FCC, RED
- RF output : 12.72 dBm
- Thickness : 0.09 in (14.2 mm)

WHAT'S INCLUDED

- D-Fi USB V2
- QRG